No. and No.		Fa atoma a
· · · · · · · · · · · · · · · · · · ·		Features:     Input: Single-phase 115 - 277 VAC
· ·	CBI1210A	Output Load: power supply 12 VDC; 10 A
The second second		<ul> <li>Output: Battery charging 12 VDC; 10 A</li> </ul>
and Sat	DC UPS	Suited for the following battery types:
and the second se		Open Lead Acid, Sealed Lead Acid, lead Gel and Ni-Cd (option) • Automatic diagnostic of battery status.
	颵 🔊 🔊 👀 👀 📖	Switching technology, output voltage 10-14.4 VDC
	CUS US E353188	Three charging levels: Boost, trickle and recovery
ALC: NO. OF THE OWNER.		Protection degree IP20 - DIN rail mountable
INDUT		
INPUT	Cat. No.	CBI1210A
	Nominal Input Voltage Voltage range	115 ~ 230 ~ 277 VAC 90 – 305 VAC
	Inrush Current ( $V_n - I_n$ nom. Load). I <sup>2</sup> t	$\leq 11 \text{ A} \leq 5 \text{ msec}$
	Frequency	47 – 63 Hz
	Input Current (115 – 230 VAC)	2.8 ~ 1.3 A
	Internal fuse (factory replaceable)	4 A
OUTPUT	External Fuse (recommended) MCB curve B	10 A
	Output Voltage (V <sub>n</sub> ) / Nominal Current (I <sub>n</sub> )	12 VDC / 10A
	Output Current $I_n$	10 A
	Efficiency (at 50% of rated current)	≥ 90 %
	Turn-On delay after applying input voltage	1 sec. (max)
	Start up with Strong Load (capacitive load)	Yes, Unlimited
PROTECTION	Dissipation power load max	17 W
	Short-circuit protection	Yes
	Over Load protection	Yes
1040	Over Voltage Output protection	Yes (typ. 35 VDC)
LOAD OUTPUT	Over Temperature protection	Yes
001F01	Output voltage (at In)	10 ~ 14.4 VDC
	Nominal current $I_{load}$	$1.1 \times \ln A \pm 5\%$
	Continuous current (without battery) $I_{load} = I_n$	10 A
	Continuous current (with battery) $I_{load}$ = $I_n$ + $I_{batt}$	20 A
	Max. Current Output Load (Main) I <sub>load</sub> (4 sec.)	30 A max.
	Max. Current Output Load (Back Up) I <sub>load</sub> (4 sec.) Push Button or Remote Input Control (RTCONN cable)	20 A max. Start From Battery Without Main
	Time Buffering; min (switch output off without main input)	∞: standard 5 min.: Require SW
	Protection alarm against total discharge	9-10V DC battery
BATTERY	Threshold alarm for battery almost flat	10-11 V DC battery
OUTPUT		
	Boost charge (25 °C) (at I <sub>n</sub> ) Max. time Bust Charge	14.4 VDC 15 h
	Min. time Bust Charge	1 min.
	Trickle charge (25 °C) (at I <sub>n</sub> )	13.75 VDC
	Jumper Configuration battery type (V cell) Ni-Cd (optional)	2.23; 2.25; 2.27; 2.30; NiCd: 1.50 (10 elem.)
	Recovery Charge	2 ~ 9 VDC
	Charging current max I <sub>batt</sub> Charging current limiting I <sub>adi</sub>	$10 \text{ A} \pm 5\%$
	Reverse battery protection	20 – 100 % / Ibatt Yes
	Sulfated battery check	Yes by Jumper
	Detection of element in short circuit	Yes
	Quiescent Current	$\leq$ 5 mA
	Charging Curve automatic: I <sub>UoUo</sub>	3 stage
OTHERS	Remote Input Control (RTCONN cable)	Boost /Trickle / Recovery
	Ambient temperature (operation)	-25 – +70°C
	De Rating Ta $> 50^{\circ}$ C	- 2.5%(ln) / °C
	Ambient temperature Storage	-40 - +85°C
	Humidity at 25°C no condensation	95%
	Cooling MTBF	Auto convention > 300.000 h (IEC 61709)

## **CBI1210A** DC UPS

The Altech DC-UPS system is built to optimize power management. The available power is automatically allocated between load and battery, supplying power to the load is the first priority. For high inrush applications the charging power will reroute automatically to the load. In this case the maximum available current on the load output is two times the value of the device rated current.

The Battery Care concept based on algorithms that achieve rapid and automatic charging, battery optimization during charging time, flat batteries recovery and real time diagnostic The Real Time Auto-diagnostic system, monitors battery faults, sulfated battery, short circuit battery elements, reverse polarity connection. battery disconnect. This conditions are detected and identified by the number of blinks of the diagnosis Led.

## **Signal Output Contacts**

Main or Backup Power	Yes
Battery Power Low	Yes
Battery Fault	Yes
Max. Current Rating (Resistive Load)	1A 30 VDC/60 VAC
Minimum Permissible Current Rating	1mA @ 5 VDC

RJ45 Connection Input/Output	
Temp. Comp. Battery (with ext. probe)	Yes - Optional
Remote monitoring display	Yes - Optional
Can Bus	No

3000 VAC

1605 VAC

500 VAC

2,5 mm2 (24-14AWG)

65x115x135 mm

0.6 kg (1.35 Lbs)

IP20

Class I

2

## Jumper for Battery Type Selection



Fast / Boost Charge

## Environment

Safety and EMC

**EMC** Directive

Charging cycle

Emission

Immunity

Insulation voltage (IN/OUT)
Insulation voltage (input / ground)
Insulation voltage (Output / ground)
Protection Class (EN/IEC 60529)
Pollution Degree Environment
Connection TB, Screw Terminal
Protection class (Ground Connected)
Dimensions (WxHxD)
2.56x4.53x5.32 in
Weight (approx.)

IEC/EN 60335-2-29 Battery charger standard compliance Safety standards compliance: EN60950 / UL1950 / CE Fire Detection and alarm compliance EN54-4 89/336/EEC DIN41773 IEC 61000-6-4 IEC 61000-6-2

The Altech DC-UPS system is designed to charge and monitor all battery types, by selecting the battery type via jumpers. The predefined curves include Open Lead Acid, Sealed Lead Acid, Gel, Ni-Cd (optional) battery types. The charging curve are programmed to automatically switch between Recovery Charge, Boost charge and Trickle charge. The continuous battery efficiency monitoring, reduces battery damage risk and allows a safe operation in permanent connection.

A compact and rugged metal case with DIN rail mounting bracket provide an easy installation and an IP20 protection.

Recovery Charge

mmmmmmm

Tickle / Float Charge