





UL and C-UL listed, CSA and BG approved

# SR125SMS **Stop Motion Sensing Unit**

- Power requirements—the SR125SMS will accept 24 VDC, 110 VAC, or 220 VAC
- Motion detection input—the SR125SMS detects the stop condition of all types of AC or DC motors by sensing the motor's back EMF across terminals Z1, Z2 and Z3
- Drive compatible—the SR125SMS will function with electronic motor control devices such as variable speed controllers, DC injection brakes, etc.
- Selectable speed limit—the SR125SMS has 1 N/O and 1 N/C outputs that are switched when motor speed reaches the adjustable preset limit (0.01 to 0.10 V) for the particular output
- Auxiliary output—the SR125SMS has 2 solid state auxiliary signaling outputs











## Application



For a full explanation of the circuit operating principle and fault detection, see "Common Circuit Examples" in the Engineering Section of this catalog.

## **Operation**







## **Terminal Connections**



# Block Diagram



# Dimensions — mm/in.











### Specifications

Electrical	All Models	SR125SMS00	SR125SMS02	SRS125SMS03				
Power Supply:	±10%	24 VDC	110 VAC	220 VAC				
Power Consumption:		≤3.5 W	≤7 VA	≤7.5 VA				
Internal Fuse:	Electronic							
Safety Inputs:	Back EMF sensing between Z1 and Z2 and Z3							
Maximum Motor Voltage:	500 VAC (0 to 60 Hz)	500 VAC (0 to 60 Hz)						
Detection Threshold:	0.01 V	0.01 V						
Relay Outputs:	1 N/O + 1 N/C switched at preset detection threshold							
Auxiliary Outputs:	2 solid state for signaling	2 solid state for signaling						
Max Switched AC:	Inductive AC-15, 1800 VA	Inductive AC-15, 1800 VA inrush, 180 VA maintained						
Max Switched DC:	Inductive DC-13, 1.2-1.5 A	Inductive DC-13, 1.2-1.5 A/24 V						
Min Switched Current/Voltage:	10 mA/17 V (provided that the contact has never been used with higher loads)							
Impulse Withstand Voltage:	4000 V							
Max Drop-Out Time:	n/a							
Max Output Fuse:	4 A slow-acting or 6 A fast	4 A slow-acting or 6 A fast-acting						
Reset Mode:	n/a	n/a						
Mechanical								
Mounting:	35 mm (1.38 in.) DIN rail	35 mm (1.38 in.) DIN rail						
Case Material:	Polyamide PA6.6	Polyamide PA6.6						
Max Wire Size:	2 x 2.5 mm (14 AWG) stra	2 x 2.5 mm (14 AWG) stranded						
Weight:	AC: 600 g (21 oz.); DC: 50	AC: 600 g (21 oz.); DC: 500 g (18 oz.)						
Color:	Red with black body	Red with black body						
External Adjustment:	Motor speed preset via po	Motor speed preset via potentiometer						
Indication:	Green = Power On	Green = Chan	Green = Channel 1 activated,					
	Green = Channel 2 activate	ed Green = CH1 ·	+ CH2 activated					
Environmental								
Enclosure Protection:	IP20 terminals, IP40 (NEM	IP20 terminals, IP40 (NEMA 1) housing						
Operating Temperature:	-10 to 55°C (14 to 131°F)	-10 to 55°C (14 to 131°F)						
Compliance								
Standards:	EN1088, EN954-1, EN292	EN1088, EN954-1, EN292, EN692, EN60204-1,						
Approvals/Listings:	CE-marked for all applicable directives, UL and C-UL, CSA, BG							
Safety Category:	Cat. 3 per EN954-1 (SR125SMS internal operation)							

Specifications are subject to change without notice.

Note: The safety contacts of the Omron STI switches are described as normally closed (N/C)—i.e., with the guard closed, actuator in place, and the machine able to be started.

#### Ordering

Model	Supply	Inputs	Outputs	Auxiliary	Part No.
SR125SMS00	24 VDC	Back EMF Sensing	1 N/O + 1 N/C	2 Solid State	44510-1250
SR125SMS02	110 VAC	Back EMF Sensing	1 N/O + 1 N/C	2 Solid State	44510-1252
SR125SMS03	230 VAC*	Back EMF Sensing	1 N/O + 1 N/C	2 Solid State	44510-1253

\*230 VAC units are available on special order. Minimum quantities may apply.



